



220V Charging Interface

特点和性能

- 可以太阳能供电，也可以市电充电；
- 体积小，机构简单，易于安装
- 高亮度 LED
- 自主运行时间长
- 多档位调节
- USB 输出 5V 500mA

Features and Benefits

- Solar Powered Directly and AC Charging
- Compact. Portable and durable
- High luminance LED
- Running long time after fully charged
- Multi file adjustment
- USB output 5V 500mA

应用

- 室内照明
- 走廊庭院照明
- 露营及业务作业
- 灾难救生照明

Application

- Indoor Lighting
- Corridor court Lighting
- Camping and field operation
- Lighting disaster lifesaving

Solar LED Lanterns WT-F010 Specification

Product Code	WT-F010
Number of LED Per Lantern	SMD2835 24PCS
Ingress Protection	IP20
AC Input	220V 50/60Hz
Solar Charging Input	DC Jack 9V
USB Output	5V 500mA
Indicator	Full Charge Indicator
LED information:	
Lamp Brightness	350 lumens for high brightness 20 Lumens for high brightness
Lamp Power	12W
Lifetime of LED	LM-80
Color Temperature	5500-6500K
Battery Information:	
Battery Type	Sealed Maintenance Free (SMF) lead acid battery
Battery Back Up	4V 6AH
AC Charging Time	20-24Hrs
Working Time	3-4Hrs with high brightness ≥ 100Hrs with low brightness
Packing Information(lamp Only):	
Unit Dimension	150*150*320
Inner Packing Size	153*153*325
outer Packing Size	635*320*345 / 8Pcs
Gross Weight Per Box	11.6Kg

Solar LED Lanterns WT-F010 Specification

Operation Information	1. Please read the instructions and fully charged before Use;
	2. Before plugging in an external battery or power supply, please make sure if the power supply is correct;
	3. During the use process, when the LED lamp brightness get dimmed and batteries become fully discharged state, in order to protect the battery, please stop using and charge it in time at this time. Shouldn't charge after the LED lamp is completely no light, because easily lead to excessive discharge battery failure extremely;
	4. Must use more than 8 hours every three months;
	5. Make the lamp off when not in use
	6. When the temperature is below 0 degrees or above 40 degrees, use and charging efficiency will be reduced;
	7. Do not go near water or rain;
Scrap products	1. In order to reduce pollution of the environment, please do not throw the battery, battery to a designated disposal agency or the designated bins.